

RF Port

2001



The port number of the RF daemon

Wired Port

2000



The port number of the HS485 daemon

HMIP Port

2010



The port number of the Homematic IP daemon

CUxD Port

8701



The port number of the CUxD daemon

Group Port

9292



The port number of the Group daemon

Callback Reg. Timeout

120



Maximum time in seconds for callback registration in the Homematic gateway.

Install Mode Duration

60



Time in seconds that the controller will be in install mode when a device discovery is initiated

Unpair Devices On Deletion



If set to true, devices are unpaired from the gateway when their corresponding things are removed. The option "factoryResetOnDeletion" also unpairs a device, so in order to avoid unpairing on deletion, both options need to be set to false!

Factory Reset Devices On Deletion



If set to true, devices are factory reset when their corresponding things are removed. Due to the factory reset, the device will also be unpaired from the gateway, even if "unpairOnDeletion" is set to false!

Buffer Size

2048



Size of the response buffer retrieved from the gateway (default 2048 kB)